

1993 Barth - Generator Maintenance

Check Point	Interval								
	Every 50 Hours	Every 100 Hours	Every 200 Hours	Every 400 Hours	Every 500 Hours	Every 800 Hours	Every 1000 Hours	Every 1 Year	Every 2 Years
Check Fuel Pipes and Clamp Bands	X								
Change Engine Oil		X							
Clean Air Cleaner Element		X							
Check Fan Belt Tightness		X							
Replace Oil Filter Cartridge			X						
Check Radiator Hoses and Clamp Bands			X						
Replace Fuel Filter Cartridge				X					
Flush Radiator					X				
Replace Fan Belt					X				
Check Valve Clearance						X			
Check Nozzle Injection Pressure							X		
Replace Air Cleaner Element								X	
Check Electrical Wiring & Loose Conns								X	
Replace Fuel Pipes & Clamp Bands									X
Replace Radiator Hoses & Clamp Bands									X
Change Radiator Coolant									X

Oil Filter Fram PH 3593A
 Fuel Filter WIX 33390; NAPA 3390
 Air Filter NAPA Gold 6270
 Fan Belt Gates 9465
 Engine Oil SAE 10W-30 or SAE 10W-40